C80301 INSTALLATION INSTRUCTIONS SHEET

START FROM HERE

- Make sure power is completely off at the fuse box.Have your fixture installed by a qualified licensed
- electrician
- Prepare everything in clear area.
- Wear gloves at all times during this installation.
- Read instructions carefully before you start assembly.
 Keep this instruction sheet for future reference.
- Keep this instruction sheet for future reference
 Technical Support:1-844-628-8368

Ensure main supply is switched off.

self-tapping screws (8).

8 Reconnect power.

2 Install the bulb (2) (not included) firmly into lampholder (1).

• Fix the straight rod (6) and the straight side plate (4) on the

3 Fit the lampshade onto lampholder with shade ring (3).

5 Fit mounting bracket (7) onto mounting surface with

6 Connect wires (9) according to colour (White to White, Black to Black). Connect all earth plug together onto

Fit ceiling plate (10) onto mounting bracket with nuts (11).

body of the fixture (1) with the parts (5).

the crossbar with green, screw to tight.

Please Note:

• All Matteo Lighting fixtures come with pre-wired module(s).

• Unless instructed to do so, please do not touch any part of the module(s) as any unnecessary contact with the module could cause permanent damage.

THIS LUMINAIRE MUST BE MOUNTED OR SUPPORTED IN A JUNCTION BOX CE LUMINAIRE DOIT ÊTRE MONTÉ OU SUPPORTÉ DANS UNE BOÎTE DE JONCTION

> Hous white House A) Fixture black 8 10 11 6 $\langle \rangle$

WARNING:

This fitting must be earthed. Disconnect power and allow fitting to cool down before cleaning or changing the lamp.

